



and interactions automation programmed by your childridges, your zeroex certainst consideration programmed and application of the programmed and applications of the programmed and progra

functional—ingle prints can but no notif the light.

The University original projects of the transfer with Smartstart, the device is able to recognize and connect with the label will applied point after fathers. With Smartstart, the device is able to recognize and connect with the label will applied point of 10 (Floresch chick the Quick one on the device. Or you can find the complete DSX code on the box. Keep the box well in case you need it.

This does not successful. It follows the submitted to remove a place to the submitted to the submitted to remove a place to the 12-zimos delaws. It follows the submitted to remove a place to the submitted to remove a place to the 12-zimos delaws. It follows the submitted to the

Operation	LED Status	Switch	
Press down	On ( blue)	Power off ( default )	
Press up	Off (blue)	Power on ( default )	
Hold	1	Dimmer up or dimmer down	
Press 2x quickly	1	Send scene 1 / scene 2	
Press 3x quickly (see below)	Green LED solid 2 seconds	Inclusion or exclusion success	
	Red LED solid 2 seconds	Inclusion or exclusion fail	
Press "down" 10x quickly	Green LED flash 3 times (configuration success) OR Red LED flash 3 times (configuration fail)	Change led status	
Press "up" 8x quickly		Change locally button function	
Press "down" 8x quickly		Restores state after power failure	
Tap-tap then hold 10 seconds	Purple LED flash	Factory reset start	
	Purple LED solid 2 seconds	Factory reset finish	

Used— Differed from the best and fine of the man best from the size of the different to the fine of the different to the fine of the different to the different

Parameters (2, sec.), Darket (Spinster)

And the Co Time (2, etc.) (Spinster)

This parameter can ensure you but a few term and where sends than an automatically after the segridication of the control of the control

t the time from maximum brightness to minim

Value-10 from Sold to Sold Or From Sold to Sold need 10.

Charmer good (early for fixed grees at ANSI)

Charmer good (early fix fixed grees at ANSI)

Charmer good (early fixed grees at ANSI)

Charmer good (early fixed grees)

Charmer good (early fixed green)

Charmer good (earl

br3A - COMMAND, CLASS, FIRMINET, WORTE, MD

If you have any questions, please contact us at ask@nie-tech.com

FCC /IC

This device complies with part 15 of the FCC and Industry Canada 
(Ilcranse-awange IRSS standards). Operation is subject to the following t

FCC INC. controller with part 5 of the FCC and industry Controller (Controller Controller Controlle

d, unintentional, or automatic power
 A CAUTION - PLEASE READ!

electrician.

 MARNING - SHOCK HAZARD

TURN OFF THE POWER to the circuit for the switch and lighting fleture at the service panel (circuit breaker) prior to installation.

ALL WIRING CONNECTIONS MUST BE MADE WITH THE POWER OFF to avoid personal injury and/or damage to the switch.

Billio of Efficient all books.

A HEDICAL COLUMENT
Please TOD'OT act this work that counted to the Support
Please TOD'OT act this work the counted to the Support
A support to the Support experient.

A WARRANTY
A WARRANTY
A WARRANTY
WARANTY
WARRANTY
WARRANTY
WARRANTY
WARRANTY
WARRANTY
WARRANTY
WARRAN consequential damage, so the above limitations may you. This warranty gives you specific rights, and you other rights which vary from state to state.

V1.0 2020.12

Possible Problem	Possible Cause	Solution
The connected LED is flashed/too bright when set it to the Minimum brightness level.	LED brightness minimum setting is incorrect.	Please set the minimum brightness level according to the manual.
<ol> <li>Couldn't pair with hub/your hub cannot recognize the device.</li> </ol>	The device needs to be resetted before pairing.	Please reset the device according to the manual.
<ol><li>The device couldn't trun lights on/off manually.</li></ol>	Wiring error	Please check the wiring diagram on the manual.
<ol> <li>The smart switch is working and the 3-way switch does not.</li> </ol>	3-way Wiring error	Please check the wiring diagram on the manual.